



# INVERTER WITH BUILT IN CHARGER

CA SERIES PM-A-0600CA



Model No.	PM-A-0600CA		PM-A-0600CA		
Output power continuous	550W		550W		
Instant Surge	1600W		1600W		
AC Output Voltage	100V/110V/115V/120VAC		100V/110V/115V/120VAC		
Regulation	± 5~10%		± 5~10%		
DC Input Voltage	10~15V		20~30V		
Charging Current	3Amp	12Amp	2Amp	10Amp	14Amp
Low Battery Alarm	10.0V		19.8V		
Low Battery Shut-Down	9.8V		19.2V		
Input Low Voltage Protection	Yes		Yes		
Input High Voltage Protection	Yes		Yes		
Reverse Polarity Protection	Yes		Yes		
Output Short Circuit Protection	Yes		Yes		
Overload Protection	Yes		Yes		
Auto Temperature Control Fan	Yes		Yes		
Inout/Output Isolated	Yes		Yes		
AVR Design	Yes		Yes		
Remote Control	Yes		Yes		
Temperature protection	50°C + 5°C		50°C + 5°C		
Output frequency	50Hz or 60Hz ± 3%		50Hz or 60Hz +3%		
Efficiency	85%		85%		
Dimensions( L x W x H mm)	420 * 210 * 90		420 * 210 * 90		
Net weight (by Kg/s)	4.5		4.5		
Accessory	Alligator Clip		Alligator Clip		
Output Waveform (Modified sine wave)					

**Power Master technology co., ltd.**

8F, 651~3 Chung-Cheng Rd. Shin-Chuang City, Taipei County, Taiwan, R.O.C.  
 Telephone No: 886-2-6626-6660, Fax No: 886-2-6626-6800

E-mail: [sales@powermaster.com.tw](mailto:sales@powermaster.com.tw), <http://www.powermaster.com.tw> &  
<http://inverters.powermaster.com.tw> & [www.b2binverters.com](http://www.b2binverters.com)